

# Relay & Contact Sensor



## OVERVIEW

The Relay & Contact Sensor is a flexible tool to build a Control4 system more effectively.

It combines the capabilities of a repeater and router with 3 contact inputs, 3 relay outputs and a temperature sensor.

The repeater function allows you to join more devices to your network and with the industry-leading performance of the Axxess HPZM Radio Module, this device adds additional router range and capability to your ZigBee network.

The repeater function allows you to join more devices to your network and provides more coverage for your ZigBee mesh network.

It is similar to the Multi Function Repeater but the addition of relay outputs.



# Relay & Contact Sensor

RCS-C4ZB-11

## WIRELESS

- Axxess HPZM Radio Module
- ZigBee PRO Compatible (802.15.4)
- Control4 Driver Downloadable
- Long range router capability; successful free range line of sight testing to 1500ft. Range will vary with indoor application.

## COMPLIANCE/APPROVALS

FCC Part 15 | IC | CE

## TEMPERATURE SENSOR

Accurate to +/- 1°C Operating range of -40°C to 70°C

## COLOR

Black | White

## REPEATER FUNCTION

Join up to 16 devices and/or extend the range of your ZigBee network.

## CONTACT SENSOR FUNCTION

3 contact sensor inputs using RJ12 jack

## RELAY FUNCTION

- 3 relay outputs using internal RJ45 jack
- DC Load Max: 1A | 60VDC
- AC Load Max: 1A | 40VAC

## POWER SUPPLY

DC power adapter is included with NA, Euro, UK or AUS/China plug.

Aux power:  
6.5V-24V AC or DC

## DIMENSIONS

W 3.1" x H " x D 2.66" 1.0  
W 7.87cm x H 6.76" x D 2.54cm

## MOUNTING

2 keyholes and screws

## DRIVERS

Download from  
[www.axxind.com/dealers/drivers](http://www.axxind.com/dealers/drivers)

## HOW TO ORDER

[axxind.com/dealers](http://axxind.com/dealers)

## POPULAR APPLICATIONS

Drape and blind controls  
Garage doors

## WHAT'S IN THE BOX

