



Zappiti Driver for Control4

Installation and Usage Guide

Revision: 1.0
Date: Tuesday, April 07, 2020
Authors: Alan Chow

Contents

Overview	2
Features	3
FAQ.....	3
Developer Information.....	3
Driver Installation.....	4
Adding the driver to your project	4
Licencing.....	7
Summary	7
STEP 1 - Creating your project on driverCentral	7
STEP 2 –Purchase driver licence	9
STEP 3 – Install and activate the driverCentral cloud driver.....	10
STEP 4 – Install Chowmain driver.....	11

Overview

Supporting almost all video and audio formats, codecs and file containers, including all modern video standards such as HDMI 2.0, Ultra HD 4K, HDR, 3D subtitles and HEVC video codec with one billion colors (10-Bit color encoding), the Zappiti 4K HDR media player range sets an entirely new standard. The top class Zappiti Duo 4K HDR is equipped with an internal 3.5" SATA HDD bay with hot swap function for huge total capacity (up to 32 TB) and offers powerful Wi-Fi 5G and Ethernet gigabit network capability. The Zappiti 4K HDR media players are compatible with most audio and video formats such as UHD ISO, BD ISO, M2TS, MKV 4K, MVC 3D with 3D subtitles, BD and UHD menus support, home theater audio (including Dolby Atmos and DTS:X) and high-resolution lossless audio files. This new player range is also compatible with Zappiti Video for the best possible home theater experience.

A premium product deserves an excellent interface to match as such the Chowmain Zappiti driver for Control4 offers full movie library access on all Control4 user interfaces including the Neeo remote and T3 touchscreens.



Features

- Transport Controls
- Ability to browse movies, tv shows and more on navigator.
- View movie information including synopsis, MPAA rating, genres, cast director and more.
- T3 Touchscreen support
- Neeo remote support
- Detection of when media playback starts and stops with feedback

FAQ

What hardware will this work on?

This driver will work on models supporting Zappiti firmware 4.23.251 and above.

Developer Information



Copyright © 2020 Chowmain Ltd.

All information contained herein is, and remains the property of Chowmain Ltd and its suppliers, if any. The intellectual and technical concepts contained herein are proprietary to Chowmain Ltd and its suppliers and may be covered by U.S. and Foreign Patents, patents in process, and are protected by trade secret or copyright law. Dissemination of this information or reproduction of this material is strictly forbidden unless prior written permission is obtained from Chowmain Ltd.


<http://www.chowmainsoft.com>

Driver Installation

1. The driver you have downloaded will be in a zip file. Double click on this file to open it in your preferred zip program (WinZip, WinRar, etc.).



2. Extract the c4z files to the My Documents\Control4\Drivers directory. If you are using Windows 7 or 8 this will be extracted to the Libraries\Documents\Control4\Drivers directory.



3. You are now ready to add and configure the driver via the Composer Pro software.

Adding the driver to your project

IMPORTANT – Before undertaking the installation of the driver please follow the licencing steps outlined at the end of this document.

1. Launch the Composer Pro application and connect to your project
2. In the 'System Design' page select the 'Search' tab on the right hand side.
3. Type in 'Zappiti' in the search field.

☒ Local
 ☐ Online
 ☐ Certified Only
 [Clear Search](#)

Category:

-- All Categories --

Type:

-- All Types --

Manufacturer:

-- All Manufacturers --

Control Method:

All Methods

 Sort:

Relevance

Zappiti

Zappiti

4/02/2020 12:00 AM

Local

4. Double click on the '**Zappiti**' driver to add it to your project
5. Highlight the '**Zappiti Player**' driver on the left hand side.
6. Type in the '**IP Address**' and click on '**Set**'.
NOTE: Static IP Address or IP reservation required.

IP Address	172.16.16.159
-------------------	---------------

7. You can also modify the button mappings via the following properties.








Button Mapping	
GUIDE	DO_NOTHING ▾
Hash Button	DO_NOTHING ▾
Star Button	DO_NOTHING ▾
CUSTOM_1	DO_NOTHING ▾
CUSTOM_2	DO_NOTHING ▾
CUSTOM_3	DO_NOTHING ▾

8. Click on the Connections tab.



9. Highlight the '**Zappiti Virtual Switcher**' driver on the left hand side.

10. Bind the audio/video outputs to the relevant inputs.

Name	Type	Connection	Input/Output	Connected To
Audio/Video Outputs				
 OUTPUT	Video	COMPOSITE	Output	LG Television->HDMI 3
 OUTPUT	Video	HDMI	Output	
 OUTPUT	Audio	STEREO	Output	
 OUTPUT	Audio	DIGITAL_OPTICAL	Output	
 OUTPUT	Audio	DIGITAL_COAX	Output	
Room Control				
 Room Selection - OUTPUT	RoomControl	AUDIO_SELECTION	Output	
 Room Selection - OUTPUT	RoomControl	VIDEO_SELECTION	Output	

11. Click on the File and Refresh Navigators. This will cause the driver to automatically hide the Virtual Switcher and other drivers accordingly from all accessible rooms.

12. Congratulations you have set up the Zappiti driver.

Licencing


Chowmain drivers require a valid licence to use the driver. Drivers can be purchased from our distributor [driverCentral](#) however all Chowmain drivers come with a 7 day trial. We recommend that prior to purchasing a driver that you test the driver out to ensure that it will work with your hardware and will meet your requirements. The licencing procedure is broken down into 4 steps. A summary of the steps are below along however we have also provided detailed steps if the summary is not sufficient.

Summary

1. Create your project on the driverCentral.io website (This will generate a specific token which you will use in the next step)
2. Download, install and activate the driverCentral cloud driver in your project (Only once per project. Use the token generated in step 1)
3. (Optional) To try a driver, simply download it and install it in your project
4. To purchase a driver:
 - a. On driverCentral, purchase a license and register it to your project
 - b. If the driver is not already installed in your project, download it and install it
 - c. If necessary, use the cloud driver's Action: "Check Drivers" to force licence download to the project.


STEP 1 - Creating your project on driverCentral

1. Visit <http://www.drivercentral.io>
2. Log into your driver Central dealer account.
3. Visit the Project Portal
4. Click on Create Project



The screenshot shows the driverCentral Project Portal interface. At the top, there is a header with the text "Click on a project or create new project" and two buttons: "Download Cloud Driver" (blue) and "Create Project" (green). Below the header is a search bar with the placeholder text "Search in table". Under the search bar, there are two columns: "Project Name" and "Status", both with a dropdown arrow. At the bottom right, there is a pagination control showing "«", "<", "1", ">", and "»".

- It will prompt you for a project name. Type in a meaningful name for your customer's project




Project Creation

Project Name

Enter Project Name

Create Project

- Click on Create Project
- Click on the project we just created to expand the project



Click on a project or create new project

Download Cloud Driver Create Project


Search in table

Project Name Status

Alan's House

« < 1 > »

- Take note of the Project Token as this will be used in STEP 3 when we install the driverCentral cloud driver.




Project Name: Alan's House	MAC Address: Not Connected to Project	Action:
Project Token: ABCDEFGHIJ	Last Communication: Not Connected	Connection Status: Not Connected

STEP 2 –Purchase driver licence


1. Visit <https://www.drivercentral.io/chowmain-ltd/> and find the product/driver you want to purchase a licence for.
2. Click on the Add to Cart button



3. Click on the Shopping Cart icon in the top right corner and click on View cart




4. Confirm that your order is correct and click on Proceed to checkout




5. Follow the prompts and click on Submit my order



6. This will take you to PayPal for payment.
7. Pay via PayPal. It will automatically return to the marketplace when confirmed.
8. You will now be at a page where you can see your purchased licence.

License Name ↕	License Key ↕	Project Assigned ↕	Action ↕
			<button>Assign to Project</button>

- From here assign the licence to the project we created or if you did not follow that step create a new project



License Assignment for
221

Assign License to Existing Project

Select Existing Project:
New Project (enter project name below) ▼

Or...

Create a new project


Enter New Project Name
Enter email for Installer Notifi

Are you sure you want to do this?
Assign License to Project?

STEP 3 – Install and activate the driverCentral cloud driver

NOTE: Only one instance of the driverCentral cloud driver installed per project. Do not install additional cloud drivers.

- Visit <http://www.drivercentral.io>
- Log into your driver Central dealer account.
- Visit the Project Portal
- Click on Download Cloud Driver



Click on a project or create new project

Download Cloud Driver Create Project

Search in table

Project Name ↕	Status ↕
« < 1 > »	

- Copy the C4Z driver to My Documents\Control4\Drivers directory.
- Add the driver to your project.

- Click on the driver to view it's properties

Cloud Status	Please enter cloud project token below...
Project Information	(1) Total, (0) Licensed, (0) Trials, (1) Expired, (0) Updates.
Driver Version	1001
Project Token	<input type="text"/>
	Project token from driverCentral.io project portal
Driver Actions	<input type="button" value="v"/>
Debug Mode	Off <input type="button" value="v"/>

- Type in the project token we took note of in STEP 1.
- Click on the Actions tab
- Click on Check Drivers

STEP 4 – Install Chowmain driver

- Install the Chowmain driver
- You will notice that the Activation Status reflects a Licence Activated state.
- Any driver that does not have a purchased licence will have a trial licence activated via the marketplace. Note that there is no way to reactivate the trial so please use wisely.
- If you do not then press the Check Drivers action in the driverCentral Cloud driver again.

Activation Status	Update Available!!! License Activated
Driver Version	1002
Driver Information	Navigate to connections tab and make serial binding
Automatic Updates	Off <input type="button" value="v"/>